

AMPLIFIER SERIES



- ◆ With 5CH MIC input, 2CH AUX input ; individual volume control.
- ◆ High impedance output and low impedance output.
- ◆ Two independent tone controls.
- ◆ MASTER control.
- ◆ Select with five zones.
- ◆ MIC 1 with broadcast priority and can automatic cut input source.
- ◆ To install the 19 "standard rack, sold separately L bracket.

Model	YT-5300PMS	YT-5400PMS	YT-5500PMS
Rated Output Power	300W	400W	500W
Input	MIC Input * 5CH 2mv-54dB at 10Kohms. AUX Input * 1CH 90mv-22dB at 100Kohms. BGM Input * 3CH.		
Output Impedance	Low impedance output --0, 4ohms, 8ohms, 16ohms. High impedance output --70V, 100V.		
Tone Control	Bass +/-10dB at 100Hz ; Treble +/-10dB at 10KHz.		
Frequency response	25Hz-18KHz (± 3dB)		
S/N Ratio	69dB		
Input voltage	AC 110V-220V 50/60Hz ; DC24V		
Weight	15.5kg	18.3kg	21.3kg
Dimensions	430W * 355D * 133H(mm)		

Dealers

INPRO INTERNATIONAL CO., LTD.

This drawing is for reference only, Dimensions in real product-based, original and retains the right to change the specifications.