



FX6-125

Model FX6-125

- ~ Output power: 125W (RMS).
- ~ Frequency response: 20Hz~22KHz.
- ~ Total harmonic distortion: 0.2%.
- ~ Noise ratio: -88dB%.
- ~ Tape input: RCA jack.
- ~ Maximum output value: 200W/4 THD 1KHz.
- ~ Auxiliary input: 6.3mm Phone jack.
- ~ Power supply: AC 110V 50/60Hz DC 24V.
- ~ Microphone input: 6.3mm Phone jack and balanced XLR 3 Pin socket.
- ~ Equipped with 6+2CH audio mixing function, MIC input*6 / AUX input *1 / TAPE input *1.
- ~ Each CH has REVERB control/treble and bass quality control/MONITOR volume/CH OUT LEVEL control.
- ~ Built-in 5-segment sound quality equalizer, the adjustment range is ~ 12dB.
- ~ Dimensions: 525W * 295D * 280H(mm).

Dealers

INPRO INTERNATIONAL CO., LTD.

This drawing is for reference only, Dimensions in real product-based, original and retains the right to change the specifications.